



Specifications Noxion LED Spot GU10  
PAR16 4W 400lm 36D - 840 Cool White  
| Replaces 50W



[View Product](#)

## General Information

|                             |  |
|-----------------------------|--|
| SKU                         | 238485                                     |
| EAN                         | 8719157014212                              |
| Brand                       | Noxion                                     |
| Manufacturer Name           | Noxion LEDspot GU10 4-50W 840 36D 400lm ND |
| Full box quantity           | 100  |
| Any Lamp all-in warranty    | 2 Years                                    |
| Energy efficiency class     | E  |
| Energy efficiency class old | A++  |
| Average Lifetime (h)        | 25000                                      |

## Technical Information

|                             |                 |
|-----------------------------|-----------------|
| Technology                  | LED             |
| Product Type Category       | GU10 LED        |
| Voltage (V)                 | 220-240         |
| Beam Angle (degree)         | 36              |
| Dimmable                    | Not Dimmable    |
| Cap / Base                  | GU10            |
| Colour Code                 | 840 Cool White  |
| Colour temperature (Kelvin) | 4000 Cool White |
| Colour Rendering (Ra)       | 80-89           |

|                          |              |
|--------------------------|--------------|
| Colour of Light          | White        |
| Light colour options     | Single Color |
| Luminous Efficacy (lm/W) | 100          |
| Type of sensor           | No Sensor    |

## Lamp Information

|        |        |
|--------|--------|
| Series | Lucent |
|--------|--------|

## Dimensions

|               |       |
|---------------|-------|
| Height (mm)   | 50    |
| Diameter (mm) | 52    |
| Shape         | Spot  |
| Exact shape   | PAR16 |

## Why Any-lamp?

 Order from the **largest lighting specialist** in Europe  **Customised** quotation

 Up to **7 years warranty**  **Easy** return process